

Path Generation

The objective of this analysis is to design a 4-bar mechanism that possesses a point that will trace out a specified path.

In the path generation synthesis problem, R_1 , R_2 , and R_3 are given, and β_2 and β_3 are given. The engineer needs to determine coupler motion angles, α_2 , and α_3 , as well as the magnitudes and directions of the left and right dyad vectors (**W**, **Z**, **W*** and **Z***).

Now, instead of expanding around column 1 (motion generation), we will expand about column 2 and proceed with exactly the same type of approach as before.

$$\begin{bmatrix} 1 & 1 & \bar{R}_1 \\ e^{ib_2} & e^{ia_2} & \bar{R}_2 \\ e^{ib_3} & e^{ia_3} & \bar{R}_3 \end{bmatrix} \begin{bmatrix} \bar{W} \\ \bar{Z} \\ -1 \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \\ 0 \end{bmatrix}$$

$$\begin{aligned} (\bar{R}_3 e^{ib_2} - \bar{R}_2 e^{ib_3}) - e^{i\alpha_2} (\bar{R}_3 - e^{ib_3} \bar{R}_1) + e^{i\alpha_3} (\bar{R}_2 - e^{ib_2} \bar{R}_1) = \\ (\bar{R}_3 e^{ib_2} - \bar{R}_2 e^{ib_3}) + e^{i\alpha_2} (-\bar{R}_3 + e^{ib_3} \bar{R}_1) + e^{i\alpha_3} (\bar{R}_2 - e^{ib_2} \bar{R}_1) \end{aligned}$$

Determine closed form solutions for α_2 and α_3 .

Set up equations to find **W** and **Z**.

How will you solve for right dyad components?